

TECHNICAL DATA

# Fluke i5sPQ3, 5 A AC Current Clamps, 3-pack



## Key features

- Low level current clamp measures up to 5 A AC
- Compact shape makes transporting and storing convenient; the clamp measures only 116 x 43 x 23 mm (4.6 x 1.7 x .9 in)
- Take accurate readings without breaking the circuit
- CAT III 600 V (For insulated conductors only)

## Product overview: Fluke i5sPQ3, 5 A AC Current Clamps, 3-pack

A pack of 3 pieces of the i5s current clamps, specially configured to provide low current accuracy while taking measurements on secondary current transformers. This cost-saving 3-pack is perfect for use with 3-phase tools such as the Fluke 434 or Fluke 435. The compact shape makes transporting and storing convenient. Takes accurate readings without breaking the circuit.

## Specifications: Fluke i5sPQ3, 5 A AC Current Clamps, 3-pack

Specifications	
Nominal current range	5 A
Continuous current range	10 mA to 6 A
Maximum non-destructive current	70 A

Lowest measurable current	10 mA	
Basic accuracy		48 Hz to 65 Hz
	10 mA to 1 A	1% + 5 mA
	1 A to 5 A	1%
Useable frequency	40 Hz to 5 kHz	
Output level(s)	400 mV/A	
Input load impedance	> 1 MΩ in parallel with up to 47 pF	
Crest factor	≤ 3, add 0.7% to accuracy	
<b>Safety specifications</b>		
Safety	CAT III 600 V per IEC/EN61010-1, Pollution Degree 2	
Maximum voltage	600 V AC	
<b>Mechanical and General Specifications</b>		
Warranty	1 year	
Maximum conductor diameter	15 mm	
Output cable length	2.5 m	
BNC adapter	Yes	
BNC to banana adapter included	No	

## Ordering information



### **Fluke i5sPQ3**

5 A ac Current Clamps, 3-pack

---



Fluke. *Keeping your world up and running.*®

**Fluke Corporation**  
PO Box 9090, Everett, WA 98206 U.S.A.

**For more information call:**  
In the U.S.A. (800) 443-5853  
In Canada (800) 36-FLUKE  
From other countries +1 (425) 446-5500  
[www.fluke.com](http://www.fluke.com)

©2024 Fluke Corporation.  
Specifications subject to change without notice.  
06/2024

**Modification of this document is not permitted  
without written permission from Fluke Corporation.**